



Specification/Open Sets-LOVOL engine



3-Phase 50Hz@1500RPM

Model			Engine Spec					Alternator	Compact Version		
Genset	Prime KVA	Prime KW	Cons.Full	Engine	Cyl.	Gov.	Asp.	Brushless	Dimension(L*W*H)	Weight	Tank
Y-L30	30kVA	24kW	6.0L/h	1003G	3	M	N/A	YDSF.I184G	1660*882*1285mm	786kG	220L
Y-L38	38kVA	31kW	7.5L/h	1003TG	3	M	N/A	YDSF.I184H	1660*882*1285mm	786kG	220L



3-Phase 50Hz@1500RPM

Model			Engine Spec					Alternator	Compact Version		
Genset	Prime KVA	Prime KW	Cons.Full	Engine	Cyl.	Gov.	Asp.	Brushless	Dimension(L*W*H)	Weight	Tank
Y-L42	42kVA	34kW	9.5L/h	1004G	4	M	N/A	YDSF.I184J	1750*840*1361mm	930kG	248L
Y-L60	60kVA	48kW	13.5L/h	1004TG	4	M	TC	YDSF.I224E	1851*882*1361mm	960kG	240L
Y-L70	70kVA	56kW	14.0L/h	1004TG	4	M	TC	YDSF.I224F	1851*882*1361mm	960kG	220L



3-Phase 50Hz@1500RPM

Model			Engine Spec					Alternator	Compact Version		
Genset	Prime KVA	Prime KW	Cons.Full	Engine	Cyl.	Gov.	Asp.	Brushless	Dimension(L*W*H)	Weight	Tank
Y-L85	85kVA	68kW	17.0L/h	1006TG1A	6	M	TC	YDSF.I224G	2150*890*1600mm	1250kG	294L
Y-L100	100kVA	80kW	20.0L/h	1006TG2A	6	M	TC	YDSF.I274C	2150*890*1600mm	1280kG	286L
Y-L130	130kVA	104kW	28.0L/h	1006TAC	6	E	TCA	YDSF.I274E	2306*948*1428mm	1360kG	310L

Specification/Soundproof Sets-LOVOL engine



3-Phase 50Hz@1500RPM

Model			Specification		Compact Version		
Genset	Prime KVA	Prime KW	Engine	Alternator	Dimension(L*W*H)	Weight	Tank
Y-L30S	30kVA	24kW	1003G	YDSF.I184G	2500*1000*1510mm	1243kG	220L
Y-L38S	38kVA	31kW	1003TG	YDSF.I184H	2500*1000*1510mm	1243kG	220L
Y-L42S	42kVA	34kW	1004G	YDSF.I184J	2500*1000*1510mm	1286kG	248L
Y-L60S	60kVA	48kW	1004TG	YDSF.I224E	2500*1000*1510mm	1425kG	240L
Y-L70S	70kVA	58kW	1004TG	YDSF.I224F	2500*1000*1510mm	1475kG	220L
Y-L85S	85kVA	68kW	1006TG1A	YDSF.I224G	3000*1160*1760mm	1900kG	294L
Y-L100S	100kVA	80kW	1006TG2A	YDSF.I274C	3000*1160*1760mm	1940kG	286L
Y-L130S	130kVA	104kW	1006TAG	YDSF.I274E	3200*1160*1760mm	2115kG	310L